



Time: 3 Hours

Marks: 80

- N.B (1) Question No. 1 is compulsory
(2) Out of remaining questions attempt three
(3) Figures to right indicate full marks.

Q1 Solve any four

- a) Compare ground wave & sky wave propagation (5)
- b) Define modulation & explain any two need of modulation (5)
- c) State in brief different types of noise. (5)
- d) With reference to receiver define sensitivity, selectivity, fidelity and image frequency rejection (5)
- e) Draw BASK & BFSK signal for 10111010. (5)

- Q2 a) Explain with neat diagram Indirect method of FM generation (10)
b) Prove Friss formula with reference to noise factor in cascade. (10)

- Q3 a) What is multiplexing in communication system? Explain in brief transmitter and receiver of FDM. (10)

- b) A sinusoidal carrier has an amplitude of 20 V & frequency of 200 KHz. It is amplitude modulated by a sinusoidal voltage of amplitude 6 V & frequency 1 KHz. Modulated voltage is developed across a 80Ω resistance. 1. Write the equation of modulated wave 2. Determine modulation index 3. Draw the spectrum of modulated wave & 4. Calculate total average power. (10)

- Q4 a) Explain generation & demodulation of PWM. (8)

- b) In an AM receiver the loaded Q of antenna circuit at the input to mixer is 100. Calculate image frequency & its rejection at 1 MHz. (8)

- c) State in brief different types of communication channel (4)

- Q5 a) Explain delta modulator transmitter & receiver with neat block diagram (10)

- b) State & prove following properties of Fourier transform.

- (i) Time shifting (ii) convolution in time domain (10)

- Q6 Write short notes (Any Four) (20)

1. Sampling theorem
2. Frequency spectrum allocation
3. Tropospheric scatter propagation
4. Inter symbol interference
5. Noise figure & noise factor